NetTV

Progressive Scan Displays

DTV34X

At the recent InfoComm Shoot-out, Net TV's DTV34x 32" viewable monitor received perfect 5 out of 5's in all 7 categories. The DTV34x has XGA resolution, multiple AV and RGB inputs, 12-watt speakers with a built in sub-woofer. It is the perfect display for the Internet, Windows applications, DVD/Multimedia, and it is HDTV and Digital-TV capable (480p, 720p and 1080i).*

** InfoComm Shoot-out categories: grayscale, color accuracy, white balance, bandwidth, sharpness, video scaling and RGB scaling.*

"...the best looking images came from NetTV's DTV34x..."
Peter H. Hutman, CTS

Specifications	
Compatibility:	480p, 720p, 1080i Digital TV broadcasts, Standard analog broadcasts, PC and Mac Computers
34" Display:	32" Viewable 2R Flat Screen, Invar Shadow Mask, Dynamic Beam Focus
RGB Signal:	XGA 1024x768 (NI), SVGA 800x600 (NI), 640x480 and 800x600 for Macintosh (*with adapter*)
RGB Inputs:	(2) VGA 15-Pin inputs (*1 front panel and 1 back panel*)
RGB Output:	(1) VGA 15-Pin output
Video Inputs:	(2) Composite RCA, (1) S-Video
Video Outputs:	(1) Composite RCA, (1) VGA
Frequency Scanning:	Horizontal: 31-50 Khz, Vertical: 50-90 Hz; 15.743 KHz/NTSC, 15.625 KHz/PAL
Audio:	Stereo, 12 watt x 2 ported speakers and built-in subwoofer
Audio Output:	(1) Stereo RCA
Dot Pitch:	0.8mm
Remote Microprocessor Controls:	Power, Channel Change, Brightness, Contrast, Sharpness, V-Size, V-Position, H-Size, H-Position, Degauss, Pincushion, Rotation, Bass, Treble, Balance, Color, Red-Blue-Green Gain, Tint, Video Modes, Volume.
Govt. Certifications:	FCC class B, UL-478, DHHS, CE
Dimensions:	34" W x 28" H x 23" D
Weight:	156 lbs
Warranty:	2 Year Parts and Labor

FCC-B

NetTV Contact Info

www.net-tv.net 2591 Kerner Blvd - San Rafael, CA -94901-9800
TEL:415/259-2820 - FAX:415/259-2828 - TOLL FREE:800/440-6388